
INSTALLATION INSTRUCTIONS



ROUND SURFACE MOUNT






LED DISK LIGHT

Provides surface mount light for new construction applications. Unit fits most 4 " junction boxes and can replace 5 ", 6" recessed can lights to elimiate baffles and fire rated boxes. It is also suitable for used in dry, damp or wet locations.

PACKAGE CONTENTS







WARNING

FOR YOUR SAFETY READ AND UNDERSTAND INSTRUCTIONS COMPLETELY BEFORE STARTING INSTALLATION. BEFORE WIRING TO POWER SUPPLY, TURN OFF ELECTRICITY AT THE FUSE OR CIRCUIT BREAKER BOX.



CAUTION: RISK OF FIRE

SUPPLY CONDUCTORS (POWER WIRES) CONNECTING THE FIXTURE MUST BE RATED MINIMUM 90°C. IF UNCERTAIN, CONSULT AN ELECTRICIAN.



CAUTION: RISK OF ELECTRIC SHOCK

DISCONNECT POWER BEFORE OR CIRCUIT BREAKER BEFORE INSTALLING OR SERVICING.

SAFETY PRECAUTIONS




FOR SAFETY READ AND UNDERSTAND INSTRUCTIONS COMPLETELY BEFORE STARTING INSTALLATION. ELECTRICITY SHOULD BE TURNED OFF AT THE FUSE OR THE CIRCUIT BREAKER BOX BEFORE INSTALLING THE FIXTURE. ALL ELECTRICAL CONNECTIONS MUST BE IN ACCORDANCE WITH N. E. C. OR YOUR LOCAL CODE.

ASSEMBLY INSTRUCTIONS


1. PREPARING FOR INSTALLATION: DISCONNECT ELECTRICAL POWER BEFORE INSTALLING OR SERVICING ANY PART OF THIS FIXTURE. 2. THIS PRODUCT SHALL BE SURFACE MOUNTED WITH JUNCTION BOX OR NON-COMBUSTIBLE SURFACE ABOVE 4 FEET (1.2 METER) HIGH. USER SHOULD PREPARE NECESSARY ACCESSORIES AND SPARE PARTS (NOT PROVIDED) INCLUDING JUNCTION BOX AND SCREWS.

INSTALLATION (CONSULT A QUALIFIED ELECTRICIAN BEFORE INSTALLING)

1. Connect supply wires to wires on fixture with wire nuts or push wires into Quick Connector. Connect white to white, black to black, and copper wire to copper wire as grounding connection.



2. Completing the installation by attaching the fixture into the mounting plate tightly to the j-box. Attach the diffuser by twisting and lock the diffuser in place.



COMPATIBLE DIMMERS

ı		. =: ((=====
ı	LUTRON	LEVITON
ĺ	• PD-6WCL	• 6681
l	• DVCL-153P	• 6672
l	• CTCL-153P	
l	• MACL-153M	
l	• TGCL-153P	
l	• LGCL-153P	
- 1		



WARNING:

Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.



www.jescolighting.com support@jescolighting.com
Tech Support: 855.592.0029

15 Harbor Park Drive Port Washington, NY 11050 Main Line: 800.527.7796 Fax Line: 855.265.5768

219 South 6th Ave City of Industry, CA 91746 Main Line: 855.654.0110 Fax Line: 626.333.2955